3. Electrical Parts List

Location no	Code no.	Description	Specifiation	Remarks
	AH26-00321A	TRANS POWER;-,-,-,-,253/230/115V,32V,1.8		MAX-KJ630
	AH26-00287E	TRANS POWER;-,MAX-DJ650,-,-,253/230/115V		MAX-KJ650
	AH39-00257F	POWER CORD;MAX980,-,CP2,250V,2.5A,1830MM		
	AH39-00320C	CBF COAXIAL CABLE;MAX-L68,110REC,-,1007#		
	AH39-40001F	CABLE-RCA;1185#26,1.2M,BLK,2P,(RED/WHITE		
	AH39-40001G	CABLE-RCA;RCA,1200MM,AWG26,GRY,10MM,1P		
	AH39-50001X	WIRE HARNESS;-,1007#24,-,-,200MM,-,-,-,-		
	AH40-00087A	TUNER-FM/AM;MJ104MA1-55C,MAX-DJ750,FM,AM		
	AH42-20001P	ANT LOOP;KS971120-01,-,18.5uH##10%,-,-		
	AH46-00031A	DISC-KARAOKE DISC (CH);12cm,-,-,MAX-KJ73		
	AH59-01198B	MICROPHONE;-,GS-66,-,-,-,-,-,-,-,MIC FOR		
	AH59-01418A	**REMOCON-ASSY;MAX-KJ650/KJ730,SAMSUNG**		
	AH59-01458A	**SPEAKER SYSTEM;PSKJ650 SPK SYSTEM**		
	AH59-01362A	**DECK;-,MAX-KJ730**		**COMMON**
	0601-001490	LED;INVERTER,BLUE,3MM,465-477NM		
	3301-000132	CORE-FERRITE;AC,28.8x19.3x7.5mm,1400,290		
	3711-003379	CONNECTOR-HEADER;NOWALL,3P,1R,2.5mm,STRA		
	3809-001009	CABLE-FLAT;30V,80C,250mm,18P,1.25mm,UL28		
	3809-001299	CABLE-FLAT;30V,80C,190MM,24P,1MM,UL20696		
	AH39-00383A	LEAD CONNECTOR ASSY;MX-DVA5,UL100#26,-,1		
	AH39-50001M	WIRE HARNESS;RING,1007#24,350MM,BLK		
	AH63-00373A	COVER-MECHA,DVD;MX-DVA5,HIPS 94HB,-,-,-		
	AH63-00779A	COVER DUST-UPPER;CMS-300,HIPS,2.0,262,27		
	AH63-00780A	COVER DUST-LOWER;CMS-300,HIPS,2.0,262,16		
	AH92-02126A	**ASSY PCB;MAX-KJ730,-**		
SVZD2	0403-000358	DIODE-ZENER;UZ5.6BSB,5.46-5.7V,500MW,DO-		
SVD1	0403-000392	DIODE-ZENER;UZP4.7B,4.4-5V,1000MW,DO-41,		
SVU6	1003-001418	IC-MOTOR DRIVER;FAN8082,DIP,8P,-,-,1MA,S		
SVU7	1003-001418	IC-MOTOR DRIVER;FAN8082,DIP,8P,-,-,1MA,S		
SVR1	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM		
X.4	2801-003716	CRYSTAL-UNIT;9.6MHz,50ppm,28-AAM,20pF,70		
DCW1	3708-000307	CONNECTOR-FPC/FFC/PIC;7P,1.25MM,ANGLE,SN		
RCN2	3708-001464	CONNECTOR-FPC/FFC/PIC;24P,1MM,STRAIGHT,S		
ACW3	3708-001692	CONNECTOR-FPC/FFC/PIC;18P,1.25MM,STRAIGH		
MCW1	3711-000631	CONNECTOR-HEADER;BOX,11P,1R,2.5mm,STRAIG		
DCW3	3711-003379	CONNECTOR-HEADER;NOWALL,3P,1R,2.5mm,STRA		
ACW4	AH39-00652A	LEAD CONNECTOR-ASSY;MAXDJ730,-,-,9P,350M		
VCW1	AH39-00653A	LEAD CONNECTOR-ASSY;MAXDJ730,-,-,8P,350M		
MJ4	AH39-20561P	LEAD CONNECTOR ASSY;-,5295,PHR,6P,150mm,		
WIRE1	AH39-50001M	WIRE HARNESS;RING,1007#24,350MM,BLK		
HS1	AH62-00062H	HEAT SINK-ASS?Y;T2,AL,-,-,-,-,-,-		
MD1	0401-001090	DIODE-SWITCHING;1SS355,80V,100MA,SOD-323		
AD7	0401-001090	DIODE-SWITCHING;1SS355,80V,100MA,SOD-323		
AD3	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150MA,SOD-3		
AD4	0401-001099	DIODE-SWITCHING;1N4148WS,75V,150MA,SOD-3		
PD1	0402-000309	DIODE-RECTIFIER;1SR154-400,400V,1A,SOD-1		
DD1	0407-000116	DIODE-ARRAY;DAP202K,80V,100mA,CK2-3,SOT-		
RD1	0407-000116	DIODE-ARRAY;DAP202K,80V,100mA,CK2-3,SOT-		
DQ1	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,		
VQ1	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,		
VQ2	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,		
VQ3	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,		
VQ4	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,		
VQ5	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,		
VQ6	0501-000002	TR-SMALL SIGNAL;KSA812,PNP,150MW,SOT-23,		
RQ1	0501-000632	TR-SMALL SIGNAL;2SB1197K,PNP,200mW,SOT-2		
RQ5	0501-000632	TR-SMALL SIGNAL;2SB1197K,PNP,200mW,SOT-2		
DQ2	0504-000128	TR-DIGITAL;-,NPN,200MW,22K/22K,SOT-23,TP		
MIC12	0801-002518	IC-CMOS LOGIC;74LCX157,2-INPUT MULTIPLEX		
MIC6	0801-002683	IC-CMOS LOGIC;74HCT245,TRANSCEIVER,TSSOP		
MIC10	1002-001294	IC-D/A CONVERTER;PCM1742KE,24BIT,TSSOP,1		
DIC1	1003-001450	IC-MOTOR DRIVER;BA5954FM,SOP,28P,300MIL,		
MIC1	1103-001334	IC-EEPROM;K524A60X81,1KX8BIT,SOP,8P,5X4M		
MIC2	1105-001535	IC-DRAM;M12L128168A-7T,4X2MX16BIT,TSOP		
MIC5	1107-001505	IC-FLASH MEMORY;49BV162AT,1Mx16/2Mx8Bit,		
AIC3	1201-000461	IC-OP AMP;4558,SOP,8P,150MIL,DUAL,20V/mV		
AIC2	1201-000461	IC-OP AMP;4558,SOP,8P,150MIL,DUAL,20V/mV		
AIC1	1201-000461	IC-OP AMP;4558,SOP,8P,150MIL,DUAL,20V/mV		
RIC3	1201-001842	IC-OP AMP;TL3472CD,SO,TP,8P,-,DUAL,-,PAL		
RIC1	1201-002059	IC-RF AMP;ES6603SF,LQFP,64P,10X10MM,SING		
REG1	1203-002877	IC-POSI.FIXED REG.;AIC1117A-50CY,SOT-223		
REG3	1203-002935	IC-POSI.ADJUST REG.;AIC1117ACE,TO-252,3P		
REG2	1203-002935	IC-POSI.ADJUST REG.;AIC1117ACE,TO-252,3P		
MIC3	1204-002224	IC-PAL/NTSC DECODER;ES6698FD,PQFP,208P,2		
ADIC1	1205-002215	IC-CODEC;STAC9460S,SSOP,28P,10.2X5.3MM,		
MIC11	1209-001547	IC-SYNTHESIZER;SAM2193,TQFP,44P,10X10MM,		
ADR1	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012		
MR19	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012		
PR1	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012		
VL1	2007-000029	R-CHIP;0ohm,5%,1/8W,TP,2012		
DR9	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608		
DR14	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608		
DR31	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608		
DR33	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608		
DR35	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608		
DR5	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608		
AR36	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608		
DR10	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608		
MR84	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608		
MR49	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608		
MR28	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608		
AR26	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608		
AR28	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608		
AR30	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608		
AR32	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608		
AR34	2007-000052	R-CHIP;10Kohm,1%,1/10W,TP,1608		
MR93	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
RR13	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
RR14	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
RR18	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
MR92	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
MR81	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
MR79	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
MR77	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
SVR26	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
SVR24	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
SVR23	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
SVR22	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
SVR21	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
RR21	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
RR20	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
RR19	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
AR6A	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
AR7A	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
AR8A	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
AR9A	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
DR16	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
DR23	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
DR24	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
DR34	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
AR11A	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
AR12A	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
AR13A	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
AR1A	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
AR2A	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
AR3A	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
AR4A	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
AR5A	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
DR38	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
MR118	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
MR12	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
MR15	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
MR50	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
MR61	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
MR62	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
MR63	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
MR73	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
DR43	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
DR44	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
MR101	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
MR11	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
MR117	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
MR116	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
MR115	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
MR114	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608		
MR66	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
MR69	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
MR70	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
SVR25	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
AR39	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
AR40	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
AR41	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
AR42	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
AR43	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
AR38	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
ADR2	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
ADR3	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
AR1	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
AR2	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
AR3	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
AR59	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
MR103	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
MR102	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
MR104	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
MR20	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
AR65	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
AR64	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
AR63	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
AR62	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
AR60	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608		
ADR4	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608		
RR2	2007-000075	R-CHIP;220ohm,5%,1/10W,TP,1608		
VR19	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608		
VR20	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608		

Location no	Code no.	Description	Specifiation	Remarks
VR21	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608		
VR22	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608		
VR23	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608		
VR24	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608		
VR13	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608		
VR14	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608		
VR15	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608		
VR16	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608		
VR17	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608		
VR18	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608		
MR99	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608		
ADR7	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608		
AR4	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608		
AR5	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608		
MR10	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608		
SVR17	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608		
SVR15	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608		
SVR14	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608		
RR7	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608		
RR5	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608		
MR8	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608		
MR72	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608		
MR71	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608		
SVR3	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608		
SVR20	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608		
SVR19	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608		
MR46	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608		
MR45	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608		
MR44	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608		
MR43	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608		
DR7	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,1608		
AR25	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608		
DR25	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608		
DR36	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608		
MR112	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608		
MR113	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608		
AR24	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608		
AR16A	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608		
AR20	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608		
AR21	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608		
AR22	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608		
AR23	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608		
SVR2	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608		
MR68	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608		
MR67	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608		
MR64	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608		
MR60	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608		
MR21	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608		
MR52	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608		
MR54	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608		
MR57	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608		
MR37	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608		
MR36	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608		
MR35	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608		
MR31	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608		
MR30	2007-000087	R-CHIP;6.8Kohm,5%,1/10W,TP,1608		
DR2	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608		
RR12	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608		
MR42	2007-000093	R-CHIP;20Kohm,5%,1/10W,TP,1608		
DR30	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608		
DR27	2007-000094	R-CHIP;22Kohm,5%,1/10W,TP,1608		
RR16	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608		
AR10	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608		
AR11	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608		
AR12	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608		
AR13	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608		
AR15	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608		
AR18	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608		
AR44	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608		
AR45	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608		
RR17	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608		
AR46	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608		
AR47	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608		
AR48	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608		
AR49	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608		
AR8	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608		
AR9	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608		
DR11	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608		
DR6	2007-000097	R-CHIP;47Kohm,5%,1/10W,TP,1608		
MR41	2007-000100	R-CHIP;68Kohm,5%,1/10W,TP,1608		
SVR9	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608		
SVR11	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608		
SVR10	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608		
MR40	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608		
MR111	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608		
DR37	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608		
DR28	2007-000109	R-CHIP;1Mohm,5%,1/10W,TP,1608		
MR24	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
MR2	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
MR18	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
MR25	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
MR3	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
MR32	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		

Location no	Code no.	Description	Specifiation	Remarks
MR17	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
MR89	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
ADR6	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
AR14A	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
DR8	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
MR1	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
MR16	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
MR33	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
MR55	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
MR6	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
MR7	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
MR5	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
MR4	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
MR34	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
MR83	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
MR74	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
MR97	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
MR95	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
MR98	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
MR94	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
MR91	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
MR90	2007-000113	R-CHIP;33ohm,5%,1/10W,TP,1608		
SVR6	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608		
PR5	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608		
PR4	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608		
MR58	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608		
SVR4	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608		
SVR5	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608		
RR3	2007-000119	R-CHIP;560ohm,5%,1/10W,TP,1608		
RR9	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608		
RR8	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608		
MR23	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608		
DR32	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608		
DR26	2007-000123	R-CHIP;1.5Kohm,5%,1/10W,TP,1608		
AR35	2007-000125	R-CHIP;3.9Kohm,5%,1/10W,TP,1608		
AR33	2007-000125	R-CHIP;3.9Kohm,5%,1/10W,TP,1608		
AR31	2007-000125	R-CHIP;3.9Kohm,5%,1/10W,TP,1608		
AR29	2007-000125	R-CHIP;3.9Kohm,5%,1/10W,TP,1608		
AR27	2007-000125	R-CHIP;3.9Kohm,5%,1/10W,TP,1608		
AR37	2007-000125	R-CHIP;3.9Kohm,5%,1/10W,TP,1608		
AR7	2007-000125	R-CHIP;3.9Kohm,5%,1/10W,TP,1608		
MR9	2007-000134	R-CHIP;33Kohm,5%,1/10W,TP,1608		
RR6	2007-000308	R-CHIP;10ohm,5%,1/8W,TP,2012		
RR4	2007-000308	R-CHIP;10ohm,5%,1/8W,TP,2012		
ADR9	2007-000308	R-CHIP;10ohm,5%,1/8W,TP,2012		
DR29	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608		
AR69	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608		
AR68	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608		
AR67	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608		
AR16	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608		
AR19	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608		
AR66	2007-000309	R-CHIP;10ohm,5%,1/10W,TP,1608		
DR1	2007-000455	R-CHIP;18Kohm,1%,1/10W,TP,1608		
DR4	2007-000483	R-CHIP;1ohm,5%,1/8W,TP,2012		
DR3	2007-000483	R-CHIP;1ohm,5%,1/8W,TP,2012		
DR13	2007-000483	R-CHIP;1ohm,5%,1/8W,TP,2012		
DR12	2007-000483	R-CHIP;1ohm,5%,1/8W,TP,2012		
PR3	2007-000608	R-CHIP;240ohm,5%,1/10W,TP,1608		
PR6	2007-000643	R-CHIP;270ohm,5%,1/10W,TP,1608		
ADR16	2007-000694	R-CHIP;3.3ohm,5%,1/8W,TP,2012		
PR2	2007-000694	R-CHIP;3.3ohm,5%,1/8W,TP,2012		
MR29	2007-000962	R-CHIP;5.1Kohm,1%,1/10W,TP,1608		
MR27	2007-000962	R-CHIP;5.1Kohm,1%,1/10W,TP,1608		
VR9	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608		
VR8	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608		
VR7	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608		
VR12	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608		
VR11	2007-001164	R-CHIP;75ohm,1%,1/10W,TP,1608		
ADR15	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608		
ADR14	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608		
ADR13	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608		
ADR11	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608		
ADR10	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608		
AR17	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608		
AR14	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608		
RN1	2011-000651	R-NET;10OHM,5%,1/16W,L,CHIP,8P,TP,32		
RN2	2011-000651	R-NET;10OHM,5%,1/16W,L,CHIP,8P,TP,32		
RN3	2011-000651	R-NET;10OHM,5%,1/16W,L,CHIP,8P,TP,32		
DC3	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608		
DC5	2203-000236	C-CER,CHIP;0.1NF,5%,50V,C0G,TP,1608		
SVC1	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608		
RC28	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608		
RC26	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608		
RC21	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608		
RC20	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608		
MC87	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608		
MC75	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608		
MC52	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608		
AC33	2203-000257	C-CER,CHIP;10nF,10%,50V,X7R,TP,1608		
RC13	2203-000315	C-CER,CHIP;0.12NF,5%,50V,C0G,TP,1608		
RC25	2203-000357	C-CER,CHIP;0.15NF,5%,50V,C0G,TP,1608		
MC36	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-		
MC74	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-		

Location no	Code no.	Description	Specifiation	Remarks
RC8	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-		
RC6	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-		
MC35	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-		
ADC2	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-		
ADC1	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-		
MC33	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-		
MC34	2203-000440	C-CER,CHIP;1nF,10%,50V,X7R,TP,1608,-		
RC10	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-		
RC11	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-		
RC12	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-		
RC9	2203-000491	C-CER,CHIP;2.2nF,10%,50V,X7R,TP,1608,-		
AC14	2203-000531	C-CER,CHIP;2.7nF,10%,50V,X7R,TP,1608,-		
AC13	2203-000531	C-CER,CHIP;2.7nF,10%,50V,X7R,TP,1608,-		
AC12	2203-000531	C-CER,CHIP;2.7nF,10%,50V,X7R,TP,1608,-		
AC11	2203-000531	C-CER,CHIP;2.7nF,10%,50V,X7R,TP,1608,-		
AC10	2203-000531	C-CER,CHIP;2.7nF,10%,50V,X7R,TP,1608,-		
AC9	2203-000531	C-CER,CHIP;2.7nF,10%,50V,X7R,TP,1608,-		
MC6	2203-000560	C-CER,CHIP;220nF,+80-20%,25V,Y5V,TP,1608		
RC27	2203-000575	C-CER,CHIP;220NF,10%,25V,X7R,TP,2012		
MC73	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608		
MC72	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608		
MC32	2203-000626	C-CER,CHIP;0.022nF,5%,50V,C0G,TP,1608		
ADC15	2203-000681	C-CER,CHIP;0.027NF,5%,50V,C0G,TP,1608		
ADC14	2203-000681	C-CER,CHIP;0.027NF,5%,50V,C0G,TP,1608		
ADC13	2203-000681	C-CER,CHIP;0.027NF,5%,50V,C0G,TP,1608		
ADC12	2203-000681	C-CER,CHIP;0.027NF,5%,50V,C0G,TP,1608		
RC14	2203-000681	C-CER,CHIP;0.027NF,5%,50V,C0G,TP,1608		
ADC16	2203-000681	C-CER,CHIP;0.027NF,5%,50V,C0G,TP,1608		
MC25	2203-000681	C-CER,CHIP;0.027NF,5%,50V,C0G,TP,1608		
MC42	2203-000681	C-CER,CHIP;0.027NF,5%,50V,C0G,TP,1608		
AC16	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608		
AC17	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608		
AC18	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608		
AC15	2203-000783	C-CER,CHIP;0.33NF,5%,50V,C0G,TP,1608		
MC3	2203-000815	C-CER,CHIP;0.033NF,5%,50V,C0G,TP,1608		
MC5	2203-000815	C-CER,CHIP;0.033NF,5%,50V,C0G,TP,1608		
MC8	2203-000815	C-CER,CHIP;0.033NF,5%,50V,C0G,TP,1608		
DC4	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608		
MC27	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608		
MC30	2203-000888	C-CER,CHIP;4.7nF,10%,50V,X7R,TP,1608		
MC50	2203-000972	C-CER,CHIP;47nF,10%,16V,X7R,TP,1608		
RC31	2203-000975	C-CER,CHIP;47nF,10%,25V,X7R,TP,1608,-		
MC12	2203-000998	C-CER,CHIP;0.047NF,5%,50V,C0G,TP,1608		
MC49	2203-000998	C-CER,CHIP;0.047NF,5%,50V,C0G,TP,1608		
MC11	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608		
MC19	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608		
MC9	2203-001052	C-CER,CHIP;0.56nF,10%,50V,X7R,TP,1608		
MC31	2203-001103	C-CER,CHIP;6.8nF,10%,50V,X7R,TP,1608,-		
RC15	2203-001222	C-CER,CHIP;0.82NF,10%,50V,X7R,TP,1608		
AC20	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608		
AC19	2203-001607	C-CER,CHIP;0.22nF,5%,50V,NP0,-,1608		
RC29	2203-001634	C-CER,CHIP;33nF,10%,50V,X7R,TP,1608,1.6m		
RC23	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,TP,1608		
RC22	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,TP,1608		
PC6	2203-001656	C-CER,CHIP;0.47nF,5%,50V,NP0,TP,1608		
DC9	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608		
MC2	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608		
RC35	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608		
PC5	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608		
MC39	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608		
MC38	2203-005065	C-CER,CHIP;1000nF,+80-20%,10V,Y5V,-,1608		
BC28	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC7	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
EC10	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
DC1	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC3	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC4	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC5	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
EC1	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC6	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC9	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC8	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
DC2	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
DC6	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC90	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC91	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC92	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
PC1	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
PC10	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
PC13	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
PC14	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC89	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC64	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC66	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC69	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC70	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC71	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC82	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC88	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
RC30	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
RC32	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
RC38	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
RC4	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		

Location no	Code no.	Description	Specifiation	Remarks
SVC2	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
SVC3	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
SVC5	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
RC3	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
PC18	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
PC20	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
PC3	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
PC9	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
RC18	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
RC19	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
RC24	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC1	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC10	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC13	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC15	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC16	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC20	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC21	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
EC9	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
EC2	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
EC3	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
EC4	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
EC5	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
EC6	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
EC7	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
EC8	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC46	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC48	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC56	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC58	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC59	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC60	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC63	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC44	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC22	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC23	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC24	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC26	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC37	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC41	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC43	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
AC34	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
AC32	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
AC28	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
AC2	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
AC1A	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC11	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC12	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
AC37	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC10	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC1	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
ADC9	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
ADC4	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
ADC3	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
AC41	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
AC38	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC13	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC21	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC22	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC23	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC24	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC25	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC26	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC27	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC20	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC14	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC15	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC16	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC17	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC18	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC19	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
BC2	2203-005148	C-CER,CHIP;100nF,10%,16V,X7R,TP,1608		
MC14	2203-005221	C-CER,CHIP;15nF,10%,50V,X7R,TP,1608,-		
MC4	2203-005221	C-CER,CHIP;15nF,10%,50V,X7R,TP,1608,-		
RC7	2401-000243	C-AL;100uF,20%,10V,GP,TP,6.3x5,5		
RC5	2401-000243	C-AL;100uF,20%,10V,GP,TP,6.3x5,5		
MC45	2401-000243	C-AL;100uF,20%,10V,GP,TP,6.3x5,5		
PC12	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5		
PC11	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5		
MC67	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5		
MC40	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5		
ADC8	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5		
ADC7	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5		
ADC6	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5		
ADC10	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5		
PC17	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m		
PC19	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m		
AC24	2401-000918	C-AL;22uF,20%,16V,GP,-,6.3x7,5		
AC25	2401-000918	C-AL;22uF,20%,16V,GP,-,6.3x7,5		
AC26	2401-000918	C-AL;22uF,20%,16V,GP,-,6.3x7,5		
AC23	2401-000918	C-AL;22uF,20%,16V,GP,-,6.3x7,5		
AC22	2401-000918	C-AL;22uF,20%,16V,GP,-,6.3x7,5		
AC21	2401-000918	C-AL;22uF,20%,16V,GP,-,6.3x7,5		

Location no	Code no.	Description	Specifiation	Remarks
ADC5	2401-001092	C-AL;330uF,20%,10V,GP,-,8x11.5,2.5m		
PC16	2401-001092	C-AL;330uF,20%,10V,GP,-,8x11.5,2.5m		
PC2	2401-001092	C-AL;330uF,20%,10V,GP,-,8x11.5,2.5m		
PC21	2401-001092	C-AL;330uF,20%,10V,GP,-,8x11.5,2.5m		
PC7	2401-001092	C-AL;330uF,20%,10V,GP,-,8x11.5,2.5m		
PC8	2401-001092	C-AL;330uF,20%,10V,GP,-,8x11.5,2.5m		
DC10	2401-001102	C-AL;330uF,20%,16V,GP,TP,8x11.5mm,5		
DC11	2401-001102	C-AL;330uF,20%,16V,GP,TP,8x11.5mm,5		
PC4	2401-001364	C-AL;470uF,20%,16V,GP,TP,10x12.5,5		
AC29	2401-001545	C-AL;47uF,20%,25V,GP,TP,6.3x7mm,2.5		
AC31	2401-001545	C-AL;47uF,20%,25V,GP,TP,6.3x7mm,2.5		
AC35	2401-001545	C-AL;47uF,20%,25V,GP,TP,6.3x7mm,2.5		
AC36	2401-001545	C-AL;47uF,20%,25V,GP,TP,6.3x7mm,2.5		
AC39	2401-001545	C-AL;47uF,20%,25V,GP,TP,6.3x7mm,2.5		
AC40	2401-001545	C-AL;47uF,20%,25V,GP,TP,6.3x7mm,2.5		
MC68	2401-001893	C-AL;100uF,20%,16V,GP,TP,6.3x7,5		
PC22	2401-001934	C-AL;220uF,20%,6.3V,GP,-,6.3x7,-		
AC4	2401-001952	C-AL;4.7uF,20%,50V,GP,TP,5x7mm,5mm		
AC5	2401-001952	C-AL;4.7uF,20%,50V,GP,TP,5x7mm,5mm		
AC6	2401-001952	C-AL;4.7uF,20%,50V,GP,TP,5x7mm,5mm		
AC30	2401-001952	C-AL;4.7uF,20%,50V,GP,TP,5x7mm,5mm		
AC3	2401-001952	C-AL;4.7uF,20%,50V,GP,TP,5x7mm,5mm		
AC27	2401-001952	C-AL;4.7uF,20%,50V,GP,TP,5x7mm,5mm		
AC7	2401-001952	C-AL;4.7uF,20%,50V,GP,TP,5x7mm,5mm		
AC8	2401-001952	C-AL;4.7uF,20%,50V,GP,TP,5x7mm,5mm		
MC81	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm		
PC15	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm		
SVC4	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm		
ADC11	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm		
MC47	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm		
MC55	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm		
PL11	2703-000125	INDUCTOR-SMD;10uH,10%,2012		
X2	2801-004284	CRYSTAL-SMD;27MHZ,10PPM,28-AAN,20PF,30OH		
ML1	3301-001069	BEAD-SMD;120ohm,1.6x0.8x0.8mm,200mA,TP,		
RL1	3301-001069	BEAD-SMD;120ohm,1.6x0.8x0.8mm,200mA,TP,		
RL2	3301-001069	BEAD-SMD;120ohm,1.6x0.8x0.8mm,200mA,TP,		
PL15	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1		
AL1	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1		
ML3	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1		
ML4	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1		
ML5	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1		
ML6	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1		
PL1	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1		
PL9	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1		
PL8	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1		
PL7	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1		
PL6	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1		
PL5	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1		
PL4	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1		
PL3	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1		
PL2	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1		
PL10	3301-001495	BEAD-SMD;120ohm,2012,2500mA,TP,115ohm/1		
MIC8	AH11-00151A	MASK ROM;HCS201,-,-,-,SOIC,-,-,-,-,125,		
	AH41-00725A	PCB;MAX-KJ730,EPOXY,2-LAYER,0,1.6T		
	AH97-00900B	**ASSY-DECK CDP;-,MXDVA5,ASSY DECK CDP**		**COMMON**
	3405-000101	SWITCH-MICRO;1.6V,1A,70gf,SPST		
	3711-000826	CONNECTOR-HEADER;BOX,2P,1R,2mm,ANGLE,SN		
	AH31-10021A	MOTOR-DC;RF-500TB,9VDC/130mA,		
	AH31-12001A	MOTOR-LOADING;FF-030PN-09210		
	AH59-00130A	DECK;-,CMS-D100,-,-,-,-,-,CMS-S21MG		
	AH30-00018A	PICK UP;SOH-D21,-,-,-,-,CMS-21MG6		
	AH92-02039F	**ASSY PCB-AMP;MM-KJ630,-**		
ABD1	0402-001258	DIODE-BRIDGE;GBU606,600V,6A,SIP-4,BK		
AIC3	1201-000191	IC-OP AMP;4558,DIP,8P,300MIL,DUAL,20V/mV		
AIC1	1201-001955	IC-POWER AMP;STK403-070,-,14P,47MM,-,30D		
AR85	2003-000455	R-METAL OXIDE(S);100ohm,5%,2W,AA,TP,4x12		
AR86	2003-000701	R-METAL OXIDE(S);470ohm,5%,2W,AA,TP,4x12		
AR56	2009-000018	R-METAL PLATE;0.22ohm,10%,5W,CL,TP,5x14x		
AR55	2009-000018	R-METAL PLATE;0.22ohm,10%,5W,CL,TP,5x14x		
AR25	2009-000018	R-METAL PLATE;0.22ohm,10%,5W,CL,TP,5x14x		
AR24	2009-000018	R-METAL PLATE;0.22ohm,10%,5W,CL,TP,5x14x		
C1	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm		
AE9	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm		
AE8	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm		
AE12	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm		
AE14	2401-000871	C-AL;220uF,20%,50V,GP,-,10x16mm,5mm		
AE6	2401-003381	C-AL;3300uF,20%,63V,GP,BK,22x40,10		
AE5	2401-003381	C-AL;3300uF,20%,63V,GP,BK,22x40,10		
ARL1	3501-001197	RELAY-MINIATURE;12VDC,0.54W,44.4MA,1FORM		
ACW2	3710-001422	CONNECTOR-SOCKET;12P,1R,2mm,ANGLE,SN		
ACW1	3710-001422	CONNECTOR-SOCKET;12P,1R,2mm,ANGLE,SN		
ACW3	3711-003359	CONNECTOR-HEADER;BOX,10P,1R,2.5mm,STRAIG		
SPK	3716-001179	TERMINAL-BLOCK;SOLDER,4P,6.3MM,60V,7A		
AL21R	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
AL21L	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
AL20R	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
AL20L	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
HS1	AH62-00102A	HEAT SINK-,POWER;MAX-VS990,AL EXTR 2.0T,		
HS2	AH62-00111F	HEAT SINK-MAIN;MAX-KJ630,AL EXTR+AL SHEE		
AD3	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		

Location no	Code no.	Description	Specifiation	Remarks
AD2	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
AD11	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
AD104	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
AD10	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
AD1	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
FD2	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
FD1	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
AD9	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
AD8	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
AD7	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
AD6	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
AD5	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
AD4	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
AD16	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
AD15	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
AD14	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
AD13	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
AD12	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
AZD1	0403-000354	DIODE-ZENER;UZ5.1B,4.8-5.4V,500MW,DO-35,		
AZD2	0403-000354	DIODE-ZENER;UZ5.1B,4.8-5.4V,500MW,DO-35,		
AZD3	0403-000357	DIODE-ZENER;UZ5.6BM,5.4-5.8V,500MW,DO-35		
AZD4	0403-000380	DIODE-ZENER;UZP13B,12.4-14.1V,1000MW,DO-		
AZD5	0403-000392	DIODE-ZENER;UZP4.7B,4.4-5V,1000MW,DO-41,		
AZD6	0403-000564	DIODE-ZENER;TZP16A,15.3-17.1V,1000MW,DO-		
AZD7	0403-000564	DIODE-ZENER;TZP16A,15.3-17.1V,1000MW,DO-		
AZD8	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,		
AQ17	0501-000294	TR-SMALL SIGNAL;KSA708-Y,PNP,800mW,TO-92		
AQ13B	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T		
AQ3A	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T		
AQ2	0501-000331	TR-SMALL SIGNAL;KSC1009-Y,NPN,800mW,TO-9		
AQ2L	0501-000331	TR-SMALL SIGNAL;KSC1009-Y,NPN,800mW,TO-9		
AQ2R	0501-000331	TR-SMALL SIGNAL;KSC1009-Y,NPN,800mW,TO-9		
AQ5L	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
AQ5R	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
AQ1R	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
AQ10	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
AQ1L	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
FQ1	0501-000422	TR-SMALL SIGNAL;KTA1273,PNP,-30V,-30V,-2		
AQ18	0501-000422	TR-SMALL SIGNAL;KTA1273,PNP,-30V,-30V,-2		
FQ2	0501-002409	TR-SMALL SIGNAL;KTC945B,NPN,625MW,T0-92,		
AQ13B	0501-002409	TR-SMALL SIGNAL;KTC945B,NPN,625MW,T0-92,		
AQ13A	0501-002409	TR-SMALL SIGNAL;KTC945B,NPN,625MW,T0-92,		
AQ9	0504-001128	TR-DIGITAL;KRA103M,PNP,400MW,22K/22K,TO-		
AQ992	0504-001128	TR-DIGITAL;KRA103M,PNP,400MW,22K/22K,TO-		
AR4	2001-000009	R-CARBON;20KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR60	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM		
AR52	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M		
AR78	2001-000038	R-CARBON;390OHM,5%,1/4W,AA,TP,2.4X6.4MM		
AR26L	2001-000110	R-CARBON;10OHM,5%,1/4W,AA,TP,2.4X6.4MM		
AR26R	2001-000110	R-CARBON;10OHM,5%,1/4W,AA,TP,2.4X6.4MM		
AR3	2001-000110	R-CARBON;10OHM,5%,1/4W,AA,TP,2.4X6.4MM		
AR88	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR22R	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR22L	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR93	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR67	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AE24	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR5	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR45	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR44	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR2	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR1A	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR1	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR63	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR37LB	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR37RB	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR52L	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR52R	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR62	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR73L	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR73R	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR92	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR3	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR37LA	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR37RA	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
ARJ21	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
ARJ21L	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
ARJ21R	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR68	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR53L	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR53R	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR95	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR96	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR97	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR79	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR71L	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR72R	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR87	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR7	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR55R	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR55L	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR90	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR8	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2M		

Location no	Code no.	Description	Specifiation	Remarks
AR10	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR16	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR47	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR6	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
\R61	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR7	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR6	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR5	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR4	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR91	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR49	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR46	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR01A	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR11	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR2	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR54R	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR54L	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR12	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR9	2001-000850	R-CARBON;560KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR37L	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR37R	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR23L	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR23R	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR42L	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR42R	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR75L	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR75R	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR89	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR94	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR40R	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR40L	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR83	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4MM		
AR84	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M		
AR14	2001-001178	R-CARBON(S);680OHM,5%,1/2W,AA,TP,2.4X6.4		
AR13	2001-001178	R-CARBON(S);680OHM,5%,1/2W,AA,TP,2.4X6.4		
AR65	2003-000008	R-METAL OXIDE(S);100ohm,5%,1W,AA,TP,3.3x		
AR80	2003-000009	R-METAL OXIDE(S);220ohm,5%,1W,AA,TP,3.3x		
FR1	2003-000554	R-METAL OXIDE(S);2.2ohm,5%,1W,AA,TP,3.3x		
AR27R	2003-000689	R-METAL OXIDE(S);4.7ohm,5%,1W,AA,TP,3.3x		
AR27L	2003-000689	R-METAL OXIDE(S);4.7ohm,5%,1W,AA,TP,3.3x		
AC610	2201-000532	C-CERAMIC,DISC;4.7NF,10%,50V,Y5P,TP,8X3.		
AC609	2201-000532	C-CERAMIC,DISC;4.7NF,10%,50V,Y5P,TP,8X3.		
AC24L	2201-000532	C-CERAMIC,DISC;4.7NF,10%,50V,Y5P,TP,8X3.		
AC23L	2201-000532	C-CERAMIC,DISC;4.7NF,10%,50V,Y5P,TP,8X3.		
AC21R	2201-000557	C-CERAMIC,DISC;0.47NF,10%,50V,SL,TP,8X3.		
AC20R	2201-000557	C-CERAMIC,DISC;0.47NF,10%,50V,SL,TP,8X3.		
AC20L	2201-000557	C-CERAMIC,DISC;0.47NF,10%,50V,SL,TP,8X3.		
AC38	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m		
AC22R	2201-000838	C-CERAMIC,DISC;0.003NF,0.25PF,50V,C0G,TP		
AC22L	2201-000838	C-CERAMIC,DISC;0.003NF,0.25PF,50V,C0G,TP		
AC21L	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP		
AC25R	2301-000375	C-FILM,LEAD-PEF;100nF,5%,50V,TP,11x12.5x		
AC25L	2301-000375	C-FILM,LEAD-PEF;100nF,5%,50V,TP,11x12.5x		
AC41	2301-000412	C-FILM,LEAD-PEF;22nF,10%,50V,TP,8x12x4mm		
AC95A	2301-000445	C-FILM,LEAD-PEF;4.7nF,5%,50V,TP,5.5x7x3m		
AE4	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5		
AE21L	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
AE21R	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
AE1	2401-000303	C-AL;100uF,20%,25V,GP,TP,6.3x11,5		
AE11	2401-000357	C-AL;100uF,20%,50V,GP,-,8x11.5,3.5m		
AE3	2401-000438	C-AL;10UF,20%,25V,GP,-,5X11,5		
AE22R	2401-000455	C-AL;10uF,20%,35V,GP,TP,4x7mm,5mm		
AE23	2401-000455	C-AL;10uF,20%,35V,GP,TP,4x7mm,5mm		
AE25	2401-000455	C-AL;10uF,20%,35V,GP,TP,4x7mm,5mm		
AE22L	2401-000455	C-AL;10uF,20%,35V,GP,TP,4x7mm,5mm		
AE18	2401-000455	C-AL;10uF,20%,35V,GP,TP,4x7mm,5mm		
AE15	2401-000455	C-AL;10uF,20%,35V,GP,TP,4x7mm,5mm		
AE7	2401-000651	C-AL;2.2uF,20%,50V,GP,TP,4x7,5		
AE20R	2401-000651	C-AL;2.2uF,20%,50V,GP,TP,4x7,5		
AE20L	2401-000651	C-AL;2.2uF,20%,50V,GP,TP,4x7,5		
AE13	2401-000830	C-AL;220uF,20%,25V,GP,TP,8x11.5,5		
AE1	2401-001895	C-AL;100uF,20%,16V,GP,TP,6.3x11,2.5		
AE19	2401-001912	C-AL;1uF,20%,50V,GP,BK,5x11mm,2mm		
FC1	2401-001952	C-AL;4.7uF,20%,50V,GP,TP,5x7mm,5mm		
AMP-PCB	AH41-00663A	PCB-FRONT;MAX-ZJ650,PENOL,1 LAYER,-,-,24		
	AH92-02039D	**ASSY PCB-AMP;MM-KJ650,-**		
ABD1	0402-001258	DIODE-BRIDGE;GBU606,600V,6A,SIP-4,BK		
AIC3	1201-000191	IC-OP AMP;4558,DIP,8P,300MIL,DUAL,20V/mV		
AIC1	1201-001963	IC-POWER AMP;STK403-100,SIP,14P,67X25.5M		
AR85	2003-000455	R-METAL OXIDE(S);100ohm,5%,2W,AA,TP,4x12		
AR86	2003-000701	R-METAL OXIDE(S);470ohm,5%,2W,AA,TP,4x12		
AR56	2009-000018	R-METAL PLATE;0.22ohm,10%,5W,CL,TP,5x14x		
AR55	2009-000018	R-METAL PLATE;0.22ohm,10%,5W,CL,TP,5x14x		
AR25	2009-000018	R-METAL PLATE;0.22ohm,10%,5W,CL,TP,5x14x		
AR24	2009-000018	R-METAL PLATE;0.22ohm,10%,5W,CL,TP,5x14x		
C1	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm		
AE9	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm		
AE8	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm		
AE12	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm		
AE10	2401-000230	C-AL;100uF,20%,100V,GP,TP,12.5x20mm		
AE14	2401-000871	C-AL;220uF,20%,50V,GP,-,10x16mm,5mm		
AE6	2401-003381	C-AL;3300uF,20%,63V,GP,BK,22x40,10		

Location no	Code no.	Description	Specifiation	Remarks
AE5	2401-003381	C-AL;3300uF,20%,63V,GP,BK,22x40,10		
ARL1	3501-001197	RELAY-MINIATURE;12VDC,0.54W,44.4MA,1FORM		
ACW2	3710-001422	CONNECTOR-SOCKET;12P,1R,2mm,ANGLE,SN		
ACW1	3710-001422	CONNECTOR-SOCKET;12P,1R,2mm,ANGLE,SN		
ACW3	3711-003359	CONNECTOR-HEADER;BOX,10P,1R,2.5mm,STRAIG		
SPK	3716-001179	TERMINAL-BLOCK;SOLDER,4P,6.3MM,60V,7A		
AL21R	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
AL21L	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
AL20R	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
AL20L	AH27-90001A	COIL-SPRING;-,2.2UH,-,-,-,SPRING,-,-,-,-		
HS1	AH62-00102A	HEAT SINK-,POWER;MAX-VS990,AL EXTR 2.0T,		
HS2	AH62-00111E	HEAT SINK-MAIN;MAX-DJ650,AL EXTRA,5.8,9		
AD3	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
AD2	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
AD11	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
AD104	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
AD10	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
AD1	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
FD2	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
FD1	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
AD9	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
AD8	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
AD7	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
AD6	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
AD5	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
AD4	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
AD16	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
AD15	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
AD14	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
AD13	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
AD12	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
AZD2	0403-000354	DIODE-ZENER;UZ5.1B,4.8-5.4V,500MW,DO-35,		
AZD1	0403-000354	DIODE-ZENER;UZ5.1B,4.8-5.4V,500MW,DO-35,		
AZD3	0403-000357	DIODE-ZENER;UZ5.6BM,5.4-5.8V,500MW,DO-35		
AZD4	0403-000380	DIODE-ZENER;UZP13B,12.4-14.1V,1000MW,DO-		
AZD5	0403-000392	DIODE-ZENER;UZP4.7B,4.4-5V,1000MW,DO-41,		
AZD6	0403-000564	DIODE-ZENER;TZP16A,15.3-17.1V,1000MW,DO-		
AZD7	0403-000564	DIODE-ZENER;TZP16A,15.3-17.1V,1000MW,DO-		
AZD8	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,		
AQ17	0501-000294	TR-SMALL SIGNAL;KSA708-Y,PNP,800mW,TO-92		
AQ13B	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T		
AQ3A	0501-000303	TR-SMALL SIGNAL;KSA733,PNP,250mW,TO-92,T		
AQ2R	0501-000331	TR-SMALL SIGNAL;KSC1009-Y,NPN,800mW,TO-9		
AQ2L	0501-000331	TR-SMALL SIGNAL;KSC1009-Y,NPN,800mW,TO-9		
AQ2	0501-000331	TR-SMALL SIGNAL;KSC1009-Y,NPN,800mW,TO-9		
AQ10	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
AQ1L	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
AQ1R	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
AQ5L	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
AQ5R	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
AQ18	0501-000422	TR-SMALL SIGNAL;KTA1273,PNP,-30V,-30V,-2		
FQ1	0501-000422	TR-SMALL SIGNAL;KTA1273,PNP,-30V,-30V,-2		
FQ2	0501-002409	TR-SMALL SIGNAL;KTC945B,NPN,625MW,TO-92,		
AQ13B	0501-002409	TR-SMALL SIGNAL;KTC945B,NPN,625MW,TO-92,		
AQ13A	0501-002409	TR-SMALL SIGNAL;KTC945B,NPN,625MW,TO-92,		
AQ9	0504-001128	TR-DIGITAL;KRA103M,PNP,400MW,22K/22K,TO-		
AQ992	0504-001128	TR-DIGITAL;KRA103M,PNP,400MW,22K/22K,TO-		
AR4	2001-000009	R-CARBON;20KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR60	2001-000016	R-CARBON(S);1OHM,5%,1/2W,AA,TP,2.4X6.4MM		
AR52	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M		
AR78	2001-000038	R-CARBON;390OHM,5%,1/4W,AA,TP,2.4X6.4MM		
AR26L	2001-000110	R-CARBON;10OHM,5%,1/4W,AA,TP,2.4X6.4MM		
AR26R	2001-000110	R-CARBON;10OHM,5%,1/4W,AA,TP,2.4X6.4MM		
AR3	2001-000110	R-CARBON;10OHM,5%,1/4W,AA,TP,2.4X6.4MM		
AR88	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR22R	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR22L	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AE24	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR67	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR93	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR44	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR45	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR5	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR2	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR1A	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR1	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR63	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR52L	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR37RB	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR37R	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR37LB	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR37L	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR52R	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR3	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR92	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR73R	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR73L	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR62	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR37LA	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR37RA	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR68	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR53L	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR53R	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		

Location no	Code no.	Description	Specifiation	Remarks
AR95	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR96	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR97	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR79	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR72R	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR71L	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR7	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR55R	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR55L	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR87	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR90	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR8	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR6	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR47	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR16	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR10	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
\R61	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR5	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR6	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR7	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR4	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR91	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR01A	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR46	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR49	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR11	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR2	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR54R	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR54L	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR12	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR9	2001-000850	R-CARBON;560KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR42R	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR42L	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR23R	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR23L	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR75L	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR75R	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR89	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR94	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR40R	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR40L	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR83	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M		
AR84	2001-001153	R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4M		
AR13	2001-001178	R-CARBON(S);680OHM,5%,1/2W,AA,TP,2.4X6.4		
AR14	2001-001178	R-CARBON(S);680OHM,5%,1/2W,AA,TP,2.4X6.4		
AR64	2003-000008	R-METAL OXIDE(S);100ohm,5%,1W,AA,TP,3.3x		
AR65	2003-000008	R-METAL OXIDE(S);100ohm,5%,1W,AA,TP,3.3x		
AR80	2003-000009	R-METAL OXIDE(S);220ohm,5%,1W,AA,TP,3.3x		
FR1	2003-000554	R-METAL OXIDE(S);2.2ohm,5%,1W,AA,TP,3.3x		
AR27R	2003-000689	R-METAL OXIDE(S);4.7ohm,5%,1W,AA,TP,3.3x		
AR27L	2003-000689	R-METAL OXIDE(S);4.7ohm,5%,1W,AA,TP,3.3x		
AC21R	2201-000368	C-CERAMIC,DISC;0.22NF,10%,50V,SL,TP,6.5X		
AC610	2201-000532	C-CERAMIC,DISC;4.7NF,10%,50V,Y5P,TP,8X3.		
AC609	2201-000532	C-CERAMIC,DISC;4.7NF,10%,50V,Y5P,TP,8X3.		
AC24L	2201-000532	C-CERAMIC,DISC;4.7NF,10%,50V,Y5P,TP,8X3.		
AC23L	2201-000532	C-CERAMIC,DISC;4.7NF,10%,50V,Y5P,TP,8X3.		
AC20L	2201-000557	C-CERAMIC,DISC;0.47NF,10%,50V,SL,TP,8X3.		
AC20R	2201-000557	C-CERAMIC,DISC;0.47NF,10%,50V,SL,TP,8X3.		
AC38	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m		
AC22L	2201-000838	C-CERAMIC,DISC;0.003NF,0.25PF,50V,C0G,TP		
AC22R	2201-000838	C-CERAMIC,DISC;0.003NF,0.25PF,50V,C0G,TP		
AC21L	2202-000806	C-CERAMIC,MLC-AXIAL;220pF,10%,50V,Y5P,TP		
AC25L	2301-000375	C-FILM,LEAD-PEF;100nF,5%,50V,TP,11x12.5x		
AC25R	2301-000375	C-FILM,LEAD-PEF;100nF,5%,50V,TP,11x12.5x		
AC41	2301-000412	C-FILM,LEAD-PEF;22nF,10%,50V,TP,8x12x4mm		
AC95A	2301-000445	C-FILM,LEAD-PEF;4.7nF,5%,50V,TP,5.5x7x3m		
AE4	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5		
AE21L	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
AE21R	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
AE1	2401-000303	C-AL;100uF,20%,25V,GP,TP,6.3x11,5		
AE11	2401-000357	C-AL;100uF,20%,50V,GP,-,8x11.5,3.5m		
AE3	2401-000438	C-AL;10UF,20%,25V,GP,-,5X11,5		
AE22R	2401-000455	C-AL;10uF,20%,35V,GP,TP,4x7mm,5mm		
AE22L	2401-000455	C-AL;10uF,20%,35V,GP,TP,4x7mm,5mm		
AE18	2401-000455	C-AL;10uF,20%,35V,GP,TP,4x7mm,5mm		
AE15	2401-000455	C-AL;10uF,20%,35V,GP,TP,4x7mm,5mm		
AE23	2401-000455	C-AL;10uF,20%,35V,GP,TP,4x7mm,5mm		
AE25	2401-000455	C-AL;10uF,20%,35V,GP,TP,4x7mm,5mm		
AE20R	2401-000651	C-AL;2.2uF,20%,50V,GP,TP,4x7,5		
AE7	2401-000651	C-AL;2.2uF,20%,50V,GP,TP,4x7,5		
AE20L	2401-000651	C-AL;2.2uF,20%,50V,GP,TP,4x7,5		
AE13	2401-000830	C-AL;220uF,20%,25V,GP,TP,8x11.5,5		
AE1	2401-001895	C-AL;100uF,20%,16V,GP,TP,6.3x11,2.5		
AE19	2401-001912	C-AL;1uF,20%,50V,GP,BK,5x11mm,2mm		
FC1	2401-001952	C-AL;4.7uF,20%,50V,GP,TP,5x7mm,5mm		
AMP-PCB	AH41-00663A	PCB-FRONT;MAX-ZJ650,PENOL,1 LAYER,-,-,24		
	AH92-02142D	**ASSY PCB-POWER;MAX-KJ650,-**		
PBD1	0402-000450	DIODE-BRIDGE;PBL403,200V,4A,DIP-4,ST		
PIC5	1201-000191	IC-OP AMP;4558,DIP,8P,300MIL,DUAL,20V/mV		
PIC4	1201-000191	IC-OP AMP;4558,DIP,8P,300MIL,DUAL,20V/mV		
PIC1	1203-001006	IC-POSI.FIXED REG.;78R05,TO-220F,4P-,PL		
PIC2	1203-001543	IC-POSI.FIXED REG.;78R33,TO-220,4P,400MI		

Location no	Code no.	Description	Specifiation	Remarks
PIC3	1203-001589	IC-POSI.FIXED REG.;278R05,TO-220F,4P,-,P		
PC6	2401-000129	C-AL;1000uF,20%,16V,GP,-,10x16mm,5		
PC7	2401-001633	C-AL;6800uF,20%,25V,GP,BK,18x35.5,7		
PC13	2401-001923	C-AL;2200UF,20%,16V,GP,BK,12.5X16,5		
PFS1	3601-000263	FUSE-CARTRIDGE;250V,3.15A,TIME-LAG,GLASS		
PCW2	3711-000631	CONNECTOR-HEADER;BOX,11P,1R,2.5mm,STRAIG		
PCW3	3711-000820	CONNECTOR-HEADER;BOX,2P,1R,2.5MM,STRAIGH		
PCW4	3711-001011	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH		
CON1	3711-002809	CONNECTOR-HEADER;BOX,8P,1R,2mm,STRAIGHT,		
VCON1	3711-002810	CONNECTOR-HEADER;BOX,9P,1R,2mm,STRAIGHT,		
PCW2	3711-003107	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH		
VJACK2	3722-002145	JACK-PIN;1P(VHS+PIN),SHIELD,NI,BLACK/YE		
VJACK1	3722-002147	JACK-PIN;3P,NI,RED/BLU/GRN,ANGLE		
PCW6	AH39-00060C	LEAD CONNECTOR;-,-,-,8P,200MM,-,-,51015-		
HL1	AH61-01521A	HOLDER-IC;MAX-ZJ650,PBT,-,-,-,BLK,-		
PR16	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
PR15	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
PR14	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
PR13	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
PR10	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
PR11	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
PR12	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
PR6	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
PR5	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
PR4	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
PR3	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
PR7	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
PR8	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
PR9	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
VR6	2001-000938	R-CARBON;68OHM,5%,1/8W,AA,TP,1.8X3.2MM		
VR4	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM		
VR3	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM		
VR2	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM		
VR1	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM		
VR5	2001-000969	R-CARBON;75OHM,5%,1/8W,AA,TP,1.8X3.2MM		
PR1	2003-000708	R-METAL OXIDE(S);47ohm,5%,1W,AA,TP,3.3x9		
PC6	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m		
PC5	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m		
PC4	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m		
PC3	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m		
PC2	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m		
PC1	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m		
PC29	2201-000783	C-CERAMIC,DISC;100NF,+80-20%,50V,Y5V,TP,		
PC30	2201-000783	C-CERAMIC,DISC;100NF,+80-20%,50V,Y5V,TP,		
VC4	2201-000783	C-CERAMIC,DISC;100NF,+80-20%,50V,Y5V,TP,		
PC26	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP		
PC25	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP		
PC24	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP		
PC18	2401-000438	C-AL;10UF,20%,25V,GP,-,5X11,5		
PC17	2401-000438	C-AL;10UF,20%,25V,GP,-,5X11,5		
PC16	2401-000438	C-AL;10UF,20%,25V,GP,-,5X11,5		
PC15	2401-000438	C-AL;10UF,20%,25V,GP,-,5X11,5		
PC14	2401-000438	C-AL;10UF,20%,25V,GP,-,5X11,5		
PC19	2401-000438	C-AL;10UF,20%,25V,GP,-,5X11,5		
PC27	2401-000438	C-AL;10UF,20%,25V,GP,-,5X11,5		
PC23	2401-000438	C-AL;10UF,20%,25V,GP,-,5X11,5		
PC22	2401-000438	C-AL;10UF,20%,25V,GP,-,5X11,5		
PC21	2401-000438	C-AL;10UF,20%,25V,GP,-,5X11,5		
PC20	2401-000438	C-AL;10UF,20%,25V,GP,-,5X11,5		
VC1	2401-001102	C-AL;330uF,20%,16V,GP,TP,8x11.5mm,5		
VC2	2401-001102	C-AL;330uF,20%,16V,GP,TP,8x11.5mm,5		
VC3	2401-001102	C-AL;330uF,20%,16V,GP,TP,8x11.5mm,5		
PC28	2401-001893	C-AL;100uF,20%,16V,GP,TP,6.3x7,5		
PC9	2401-001895	C-AL;100uF,20%,16V,GP,TP,6.3x11,2.5		
PC8	2401-001895	C-AL;100uF,20%,16V,GP,TP,6.3x11,2.5		
PC11	2401-001895	C-AL;100uF,20%,16V,GP,TP,6.3x11,2.5		
PC10	2401-001895	C-AL;100uF,20%,16V,GP,TP,6.3x11,2.5		
	AH41-00699A	PCB-POWER;MAX-KJ730,PANEL,1 LAYER,-,-,16		
	AH92-02247A	**ASSY PCB-FRONT;MAX-KJ650,-**		
LED1	0601-001490	LED;INVERTER,BLUE,3MM,465-477NM		
MO1	0609-001189	MODULE REMOCON;HORIZONTAL,16.4MM,TR		
IC4	1201-001572	IC-PREAMP;2011,SIP,7P,17MIL,SINGLE,47,PL		
SIC01	1204-002110	IC-SOUND PROCESSOR;NJM2072D,DIP,8P,-,PLA		
UC1	2101-001052	VR-ROTARY;10KOHM,10%,0.05W,TOP		
UC01A	2201-000557	C-CERAMIC,DISC;0.47NF,10%,50V,SL,TP,8X3.		
UX1	2801-001394	CRYSTAL-UNIT;32.768KHz,20ppm,28-AAY,12.5		
UX2	2802-001174	RESONATOR-CERAMIC;10MHZ,0.5%,BK,8X3.5X3M		
UVR1	3406-001047	SWITCH-ROTARY;5V DC,0.5mA,-,12mm		
UVR5	3406-001050	SWITCH-ROTARY;5V DC,0.5mA,click,12mm		
UVR4	3406-001050	SWITCH-ROTARY;5V DC,0.5mA,click,12mm		
UVR3	3406-001050	SWITCH-ROTARY;5V DC,0.5mA,click,12mm		
UVR2	3406-001050	SWITCH-ROTARY;5V DC,0.5mA,click,12mm		
CON5	3708-000178	CONNECTOR-FPC/FFC/PIC;16P,1.25MM,ANGLE,S		
CON6B	3708-000448	CONNECTOR-FPC/FFC/PIC;6P,1.25MM,STRAIGHT		
CON6A	3708-000448	CONNECTOR-FPC/FFC/PIC;6P,1.25MM,STRAIGHT		
MCW1	3708-001195	CONNECTOR-FPC/FFC/PIC;27P,1.25MM,STRAIGH		
UCW2	3708-001946	CONNECTOR-FPC/FFC/PIC;18P,1.25MM,STRAIGH		
UCW7	3711-001062	CONNECTOR-HEADER;BOX,6P,1R,2mm,STRAIGHT,		
JACK6	3722-001190	JACK-PHONE;9P/2C,6.43PI,AU,BLK,RC6701(EI		
JACK7	3722-001190	JACK-PHONE;9P/2C,6.43PI,AU,BLK,RC6701(EI		
JACK3	3722-001588	JACK-PHONE;7P,3.6PI,AG,BLK,-		
VFD	AH07-00120A	VF DISPLAY;HNA-12LS06,MAX-ZJ550,90X40,1/		

Location no	Code no.	Description	Specifiation	Remarks
UIC1	AH11-00124A	MASK ROM;LC876748C-54N3,MAX-DJ650,56K,-		
CON27	AH39-00060A	LEAD CONNECTOR ASSY;-,51015-08,51004-08,		
UCW8	AH39-00353A	LEAD CONNECTOR ASSY;MM-Z100,1007#28,-,6P		
MCON1	AH39-20008P	LEAD CONNECTOR ASSY;5264,5395,2P,250MM,1		
W1	AH39-50001H	WIRE HARNESS;RING,1007#24,100MM,BLK		
W2	AH39-50001L	WIRE HARNESS;RING,1007#24,200MM,BLK		
H-VFD	AH61-01520A	HOLDER-VFD;MAX-ZJ650,ABS ,-,-,-,BLK,-		
	AH81-01327Y	A/S PART-FRONT;MM-ZJ650,FRONT PCB ASS'Y,		
UD4	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD3	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD24	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD23	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD21	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD9	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD8	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD7	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD6	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD5	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD20	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD12	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD11	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD10	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD1	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
LD01A	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD2	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD17	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD16	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD14	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD13	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
UD22	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
UD19	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
UD18	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
UD13	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
UQ4	0501-000422	TR-SMALL SIGNAL;KTA1273,PNP,-30V,-30V,-2		
UQ3	0501-000422	TR-SMALL SIGNAL;KTA1273,PNP,-30V,-30V,-2		
UQ2	0501-000422	TR-SMALL SIGNAL;KTA1273,PNP,-30V,-30V,-2		
UQ5	0501-002375	TR-SMALL SIGNAL;KTC8050,NPN,625MW,T0-92,		
UQ1A	0501-002409	TR-SMALL SIGNAL;KTC945B,NPN,625MW,T0-92,		
UQ1	0501-002409	TR-SMALL SIGNAL;KTC945B,NPN,625MW,T0-92,		
LQ1	0501-002409	TR-SMALL SIGNAL;KTC945B,NPN,625MW,T0-92,		
UQ9	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-		
UQ8	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-		
UQ7	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-		
UQ10	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-		
UQ11	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-		
UQ6	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-		
ULED6	0601-001238	LED;ROUND,RED,3.1mm,697nm		
ULED7	0601-001238	LED;ROUND,RED,3.1mm,697nm		
ULED8	0601-001238	LED;ROUND,RED,3.1mm,697nm		
ULED9	0601-001238	LED;ROUND,RED,3.1mm,697nm		
ULED5	0601-001238	LED;ROUND,RED,3.1mm,697nm		
ULED4	0601-001238	LED;ROUND,RED,3.1mm,697nm		
ULED3	0601-001238	LED;ROUND,RED,3.1mm,697nm		
ULED2	0601-001238	LED;ROUND,RED,3.1mm,697nm		
ULED10	0601-001238	LED;ROUND,RED,3.1mm,697nm		
UR6A	2001-000003	R-CARBON;330ohm,5%,1/8W,AA,TP,1.8x3.2mm		
UR2	2001-000005	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8x3.2mm		
SR01	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
SR02	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR14	2001-000119	R-CARBON;680OHM,5%,1/4W,AA,TP,2.4X6.4MM		
UR13	2001-000119	R-CARBON;680OHM,5%,1/4W,AA,TP,2.4X6.4MM		
UR12	2001-000119	R-CARBON;680OHM,5%,1/4W,AA,TP,2.4X6.4MM		
UR96	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR93	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR20	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KFR3	2001-000221	R-CARBON;1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR94	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR11	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR100	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KFR4	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KFR12	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR43	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR3	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR21	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KFR5	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KFR13	2001-000258	R-CARBON;1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR78	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR85	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR88	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR92	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR19	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR1A	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR228	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR40	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
KFR9	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
SR03	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR10	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
KFR17	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
KFR1	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
DR02	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
DR01	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR5A	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR60	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		

Location no	Code no.	Description	Specifiation	Remarks
UR61	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR62	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR63	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR64	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR4A	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR50	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR54	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR56	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR57	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR59	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR71	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR72	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR73	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR7A	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR8	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR91	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR65	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR66	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR67	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR68	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR69	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR70	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR26	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR27	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR28	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR31	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR32	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR33	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR104	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR108	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR16	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR17	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR24	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR25	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR41	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR42	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR44	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR48	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR49	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR39	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR35	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR36	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR34	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR37	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR38	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR53	2001-000295	R-CARBON;10MOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR224	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR95	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR6	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR5	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR4	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR106	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
KFR10	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR30	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR52	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR55	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR76	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR79	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR29	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
KFR2	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UJW84	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR150	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR233	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR82	2001-000435	R-CARBON;1MOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR58	2001-000435	R-CARBON;1MOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR84	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR83	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR51	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR7	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR22	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR105	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KFR6	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KFR14	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR223	2001-000508	R-CARBON;220KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR2B	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR90	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR18	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR45	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR23	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR227	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KFR7	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KFR15	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR99	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR98	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR97	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR87	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR2A	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR222	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR1A	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR15	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR103	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
LR2	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR225	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		

Location no	Code no.	Description	Specifiation	Remarks
UR221	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR220	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR119	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR118	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR89	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR81	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR77	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR74	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR226	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR117	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR102	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR109	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR110	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR111	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR112	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR116	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR115	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR114	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR113	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR101	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m		
UR107	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m		
UR80	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m		
KFR8	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m		
KFR16	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m		
UR47	2001-000850	R-CARBON;560KOHM,5%,1/8W,AA,TP,1.8X3.2M		
UR46	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
KFR11	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR9	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
UR231	2001-001004	R-CARBON;82OHM,5%,1/4W,AA,TP,2.4X6.4MM		
UR232	2001-001004	R-CARBON;82OHM,5%,1/4W,AA,TP,2.4X6.4MM		
UR230	2001-001004	R-CARBON;82OHM,5%,1/4W,AA,TP,2.4X6.4MM		
UR229	2001-001004	R-CARBON;82OHM,5%,1/4W,AA,TP,2.4X6.4MM		
LR1	2001-001165	R-CARBON(S);56OHM,5%,1/2W,AA,TP,2.4X6.4M		
UC2	2103-000341	VR-SEMI;2Kohm,30%,1/10W,TOP		
UC7	2201-000300	C-CERAMIC,DISC;1NF,20%,50V,Y5T,TP,5X3MM,		
UC6	2201-000300	C-CERAMIC,DISC;1NF,20%,50V,Y5T,TP,5X3MM,		
UC5	2201-000300	C-CERAMIC,DISC;1NF,20%,50V,Y5T,TP,5X3MM,		
UC3	2201-000300	C-CERAMIC,DISC;1NF,20%,50V,Y5T,TP,5X3MM,		
UC10	2201-000300	C-CERAMIC,DISC;1NF,20%,50V,Y5T,TP,5X3MM,		
UC8	2201-000389	C-CERAMIC,DISC;0.022NF,5%,50V,C0G,TP,5X3		
UC20	2201-000389	C-CERAMIC,DISC;0.022NF,5%,50V,C0G,TP,5X3		
UC12	2201-000470	C-CERAMIC,DISC;0.33NF,10%,50V,SL,TP,6.5X		
UC1A	2201-000470	C-CERAMIC,DISC;0.33NF,10%,50V,SL,TP,6.5X		
UC2A	2201-000470	C-CERAMIC,DISC;0.33NF,10%,50V,SL,TP,6.5X		
UC01B	2201-000557	C-CERAMIC,DISC;0.47NF,10%,50V,SL,TP,8X3.		
UC13	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m		
UC14	2201-000565	C-CERAMIC,DISC;47nF,+80-20%,-,,-,12.5x4m		
UC02A	2202-000231	C-CERAMIC,MLC-AXIAL;0.33NF,10%,50V,Y5P,T		
UC25A	2202-000806	C-CERAMIC,MLC-AXIAL;220pF,10%,50V,Y5P,TP		
SC02	2301-000402	C-FILM,LEAD-PEF;1nF,5%,50V,TP,5x7x2.8mm,		
SC01	2301-000419	C-FILM,LEAD-PEF;27nF,10%,50V,TP,7.5x10.5		
UC16	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
UC15	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
SC03	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5		
UC18	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5		
UC19	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5		
UC21	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5		
UC26	2401-000598	C-AL;1uF,20%,50V,GP,TP,4x7,5		
UC28	2401-000651	C-AL;2.2uF,20%,50V,GP,TP,4x7,5		
UC9	2401-000759	C-AL;220nF,20%,50V,GP,TP,5x11mm,5mm		
LC1	2401-000914	C-AL;22uF,20%,16V,GP,TP,5x11,5		
UC23	2401-001022	C-AL;3.3UF,20%,50V,GP,TP,5X11,5		
UC4	2401-001022	C-AL;3.3UF,20%,50V,GP,TP,5X11,5		
UC11	2401-001355	C-AL;470uF,20%,10V,GP,TP,8x11.5mm,5		
UC24	2401-001355	C-AL;470uF,20%,10V,GP,TP,8x11.5mm,5		
UC17	2401-001893	C-AL;100uF,20%,16V,GP,TP,6.3x7,5		
UC25	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm		
UC27	2401-001975	C-AL;47uF,20%,16V,GP,TP,5x11mm,5mm		
UL2	2701-000111	INDUCTOR-AXIAL;100UH,10%,2534		
UL1	2701-000111	INDUCTOR-AXIAL;100UH,10%,2534		
RESEVE	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW1	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW10	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW11	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
OP/CL	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
NO:0-NO:9	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
DISC1-3	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
DISC CHAN	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
CANCEL	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW12	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW3	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW29	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW28	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW27	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW26	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW25	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW30	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW9	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW8	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW7	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW6	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW5	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW4	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		

Location no	Code no.	Description	Specifiation	Remarks
USW18	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW17	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW16	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW15	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW14	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW13	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW19	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW24	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW23	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW22	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW21	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW20	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
USW2	3404-000165	SWITCH-TACT;12V,50mA,160gf,6x6mm,SPST		
FRONT	AH41-00756A	PCB-FRONT;MAX-KJ650,PENOL,1 LAYER,0,T1.6		
	AH92-02248B	**ASSY PCB-MAIN;MAX-KJ630,-**		
PIC11	0904-001621	IC-I/O CONTROLLER;PT8300,16BIT,SOP,28P,3		
DIC1	1201-000191	IC-OP AMP;4558,DIP,8P,300MIL,DUAL,20V/mV		
FIC1	1201-000191	IC-OP AMP;4558,DIP,8P,300MIL,DUAL,20V/mV		
KIC1	1201-000191	IC-OP AMP;4558,DIP,8P,300MIL,DUAL,20V/mV		
DIC1	1201-001899	IC-PREAMP;HA12237F,QFP,40P,7X7MM,-,-,PLA		
PIC2	1203-000242	IC-POSI.FIXED REG.;7812,TO-220,3P,-,PLAS		
PIC4	1203-000276	IC-POSI.FIXED REG.;7805,TO-220,3P,-,PLAS		
PIC3	1203-000299	IC-POSI.FIXED REG.;7809,TO-220,3P,-,PLAS		
KIC2	1204-001730	IC-ECHO;M65855P,DIP,16P,300MIL,PLASTIC		
FIC1A	1204-002219	IC-SOUND PROCESSOR;BD3872FS,SOP,32P,13.6		
PPC1	2201-002128	-CERAMIC,DISC;4.7NF,20%,400V,Y5U,BK,15X		
PPC2	2201-002128	-CERAMIC,DISC;4.7NF,20%,400V,Y5U,BK,15X		
PC7	2401-001067	C-AL;3300uF,20%,42V,GP,-,18x35.5,7.		
REALY	3501-001008	RELAY-POWER;12VDC,530MW,10000MA,1FORMC,1		
PPF7	3601-000216	FUSE-CARTRIDGE;250V,2.5A,TIME-LAG,GLASS,		
	3601-000248	FUSE-CARTRIDGE;250V,2A,TIME-LAG,GLASS,5x		
PPF5	3601-000414	FUSE-CARTRIDGE;250V,5A,SLOW-BLOW,GLASS,5		
PPF6	3601-000414	FUSE-CARTRIDGE;250V,5A,SLOW-BLOW,GLASS,5		
TCW1	3708-000412	CONNECTOR-FPC/FFC/PIC;12P,1.25MM,ANGLE,-		
MCW1	3708-001195	CONNECTOR-FPC/FFC/PIC;27P,1.25MM,STRAIGH		
PPCW2	3711-000190	CONNECTOR-HEADER;1WALL,2P,1R,7.92MM,STRA		
MCON2	3711-000820	CONNECTOR-HEADER;BOX,2P,1R,2.5MM,STRAIGH		
DCW1	3711-001054	CONNECTOR-HEADER;BOX,6P,1R,2.5mm,STRAIGH		
MCW2	3711-002809	CONNECTOR-HEADER;BOX,8P,1R,2mm,STRAIGHT,		
CW01	3711-002809	CONNECTOR-HEADER;BOX,8P,1R,2mm,STRAIGHT,		
DCW3	3711-003107	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH		
DCW2	3711-003409	CONNECTOR-HEADER;BOX,3P,1R,2mm,STRAIGHT,		
AW01	3711-004110	CONNECTOR-HEADER;3WALL,12P,1R,2MM,STRAIG		
AW02	3711-004110	CONNECTOR-HEADER;3WALL,12P,1R,2MM,STRAIG		
AJACK	3722-000377	JACK-PIN;4P/2C,3.5mm,SN,BLK,#16~22		
MJACK	3722-000377	JACK-PIN;4P/2C,3.5mm,SN,BLK,#16~22		
	3811-000122	WIRE-PVC CU;BCWA,300V,150mm,7/0.16mm,#26		
	6003-001375	SCREW-TAPTITE;BH,+,B,M3.L8,ZPC(YEL),SWRC		
DL4	AH26-00227A	TRANS RF;-,-,-,-,-,-,-,105KHZ,7.6 X 7.6,-		
DL1	AH26-10002W	TRANS TRAP-COIL;BIAS-TRAP105K,BIAS-TRAP,		
DL2	AH26-10002W	TRANS TRAP-COIL;BIAS-TRAP105K,BIAS-TRAP,		
PPL2	AH27-10001F	COIL-CHOKE;27uH,K,Q30,-,-,DR(6.5*7.5),-,		
PPL1	AH27-10001F	COIL-CHOKE;27uH,K,Q30,-,-,DR(6.5*7.5),-,		
PCW1	AH39-00338A	LEAD CONNECTOR ASSY;MX-G65V,#1007,22AWG,		
WR1	AH39-50001L	WIRE HARNESS;RING,1007#24,200MM,BLK		
HS1	AH62-00113A	HEAT SINK-TR;MAX-ZJ650,AL ,3.0,-,-,-,-,-		
	AH81-01327X	A/S PART-POWER;MM-ZJ650,POWER PCB ASS'Y,		
	AH81-01327Z	A/S PART-MAIN;MM-ZJ650,MAIN PCB ASS'Y,-,		
KD1	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
KD2	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
VD1A	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
VD2A	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
FD1	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
DD1	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
DD1A	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
DV2A	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
ED1	0401-000101	DIODE-SWITCHING;1N4148,75V,150MA,DO-35,T		
PD5	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
MJ61	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
ED2	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP		
PD4	0402-000151	DIODE-RECTIFIER;1N5392,100V,1.5A,DO-15,T		
PD3	0402-000151	DIODE-RECTIFIER;1N5392,100V,1.5A,DO-15,T		
PD2	0402-000151	DIODE-RECTIFIER;1N5392,100V,1.5A,DO-15,T		
PD1	0402-000151	DIODE-RECTIFIER;1N5392,100V,1.5A,DO-15,T		
KZD1	0403-000354	DIODE-ZENER;UZ5.1B,4.8-5.4V,500MW,DO-35,		
FZD2	0403-000354	DIODE-ZENER;UZ5.1B,4.8-5.4V,500MW,DO-35,		
FREE	0403-000393	DIODE-ZENER;UZP5.1B,4.8-5.4V,1000MW,DO-4		
FZD1	0403-000396	DIODE-ZENER;UZP6.8B,6.4-7.2V,1000MW,DO-4		
TZD1	0403-000399	DIODE-ZENER;UZP9.1B,8.5-9.6V,1000MW,DO-4		
DQ9	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,		
DQ8	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,		
DQ7	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,		
DQ6	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,		
DQ4	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-		
KQ2	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
DVQ2	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
DVQ1	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9		
PQ5	0501-000422	TR-SMALL SIGNAL;KTA1273,PNP,-30V,-30V,-2		
PQ3	0501-000422	TR-SMALL SIGNAL;KTA1273,PNP,-30V,-30V,-2		
PQ2A	0501-000422	TR-SMALL SIGNAL;KTA1273,PNP,-30V,-30V,-2		
DQ3	0501-000422	TR-SMALL SIGNAL;KTA1273,PNP,-30V,-30V,-2		
PQ4	0501-002409	TR-SMALL SIGNAL;KTC945B,NPN,625MW,T0-92,		

Location no	Code no.	Description	Specifiation	Remarks
PQ2	0501-002409	TR-SMALL SIGNAL;KTC945B,NPN,625MW,T0-92,		
PQ1	0501-002409	TR-SMALL SIGNAL;KTC945B,NPN,625MW,T0-92,		
FQ1	0501-002409	TR-SMALL SIGNAL;KTC945B,NPN,625MW,T0-92,		
DQ2	0501-002409	TR-SMALL SIGNAL;KTC945B,NPN,625MW,T0-92,		
KQ4	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-		
KQ3	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-		
FREE	0504-001128	TR-DIGITAL;KRA103M,PNP,400MW,22K/22K,TO-		
DQ5	0504-001128	TR-DIGITAL;KRA103M,PNP,400MW,22K/22K,TO-		
KR28	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR24	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
DVR9	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
DVR8	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
CR3	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
DSR1	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
DSR2	2001-000008	R-CARBON;15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
PR5	2001-000019	R-CARBON(S);10OHM,5%,1/2W,AA,TP,2.4X6.4M		
FR11	2001-000027	R-CARBON;100OHM,5%,1/4W,AA,TP,2.4X6.4MM		
KR22	2001-000118	R-CARBON(S);180OHM,5%,1/2W,AA,TP,2.4X6.4		
JW103	2001-000241	R-CARBON;1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR25	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR24	2001-000273	R-CARBON;100KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR27	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR2A	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
TR1	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
TR2	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
TR3	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
TR6	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
DR1	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
DR17	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
DR2	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR26	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
DR4	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
DR3	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR23	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR26	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR30	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
TR12A	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR20	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
DR24	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
ER1	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
ER2	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR1A	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
DR9	2001-000302	R-CARBON;10OHM,5%,1/8W,AA,TP,1.8X3.2MM		
DR11	2001-000302	R-CARBON;10OHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR25	2001-000319	R-CARBON;120KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR18	2001-000319	R-CARBON;120KOHM,5%,1/8W,AA,TP,1.8X3.2M		
TR12	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
TR9	2001-000331	R-CARBON;12KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
CR1	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
CR2	2001-000411	R-CARBON;18KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
MJ64	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
DR10	2001-000435	R-CARBON;1MOHM,5%,1/8W,AA,TP,1.8X3.2MM		
PR3	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
PR6	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
PR7	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
PR2	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR2	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR1	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DR6	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DR13	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DVR3	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM		
DVR14	2001-000515	R-CARBON;220OHM,5%,1/8W,AA,TP,1.8X3.2MM		
PR7A	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR29	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR21	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
CR3	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
CR5	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
DR5	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR5	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR7	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FREE	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR12	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR15	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR7	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR8	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR4	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DR20	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DVR01	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DVR10	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DVR6	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DVR7	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
ER3	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR2	2001-000591	R-CARBON;3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FREE	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DR28A	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DR21	2001-000613	R-CARBON;3.9KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR13	2001-000645	R-CARBON;330KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DR7	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
DVR13	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
DVR2	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
DR14	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR7A	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR11	2001-000660	R-CARBON;33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		

Location no	Code no.	Description	Specifiation	Remarks
AR8	2001-000689	R-CARBON;390KOHM,5%,1/8W,AA,TP,1.8X3.2M		
AR7	2001-000689	R-CARBON;390KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR12	2001-000702	R-CARBON;39KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
PR1	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR27	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR18	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
PR1A	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
PR8	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
TR10	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
TR11	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DR29	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DR12	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DR15	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DR16	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DR22	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DR25	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DR27	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DR28	2001-000734	R-CARBON;4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR14	2001-000773	R-CARBON;470KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR13	2001-000773	R-CARBON;470KOHM,5%,1/8W,AA,TP,1.8X3.2M		
FR23	2001-000773	R-CARBON;470KOHM,5%,1/8W,AA,TP,1.8X3.2M		
KR3A	2001-000780	R-CARBON;470OHM,5%,1/8W,AA,TP,1.8X3.2MM		
DVR5	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR3	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR6	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
VR15	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
VR4	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR11	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR3	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
AR4	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
DR19	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
DVR11	2001-000786	R-CARBON;47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR19	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m		
AR5	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m		
TR4	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR21	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
FR20	2001-000864	R-CARBON;56KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
DR37	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DR36	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DR35	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DR34	2001-000890	R-CARBON;6.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DR33	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR4	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR5	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM		
DR32	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM		
DR31	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM		
DR30	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM		
KR19	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DR8	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DR26	2001-000977	R-CARBON;8.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
DR18	2001-001077	R-CARBON(S);150OHM,5%,1/2W,AA,TP,2.4X6.4		
PR4	2003-000587	R-METAL OXIDE(S);22ohm,5%,1W,AA,TP,3.3x9		
DR23	2008-000140	R-FUSIBLE;2.2ohm,5%,1/2W,AA,TP,3.5x9.4mm		
KC4	2201-000300	C-CERAMIC,DISC;1NF,20%,50V,Y5T,TP,5X3MM,		
KC3	2201-000300	C-CERAMIC,DISC;1NF,20%,50V,Y5T,TP,5X3MM,		
DC29	2201-000300	C-CERAMIC,DISC;1NF,20%,50V,Y5T,TP,5X3MM,		
DC1	2201-000300	C-CERAMIC,DISC;1NF,20%,50V,Y5T,TP,5X3MM,		
DC18	2201-000300	C-CERAMIC,DISC;1NF,20%,50V,Y5T,TP,5X3MM,		
DC19	2201-000300	C-CERAMIC,DISC;1NF,20%,50V,Y5T,TP,5X3MM,		
DC33	2201-000368	C-CERAMIC,DISC;0.22NF,10%,50V,SL,TP,6.5X		
FC3	2201-000368	C-CERAMIC,DISC;0.22NF,10%,50V,SL,TP,6.5X		
FC6	2201-000368	C-CERAMIC,DISC;0.22NF,10%,50V,SL,TP,6.5X		
KC7	2201-000368	C-CERAMIC,DISC;0.22NF,10%,50V,SL,TP,6.5X		
KC8	2201-000368	C-CERAMIC,DISC;0.22NF,10%,50V,SL,TP,6.5X		
AC1	2201-000368	C-CERAMIC,DISC;0.22NF,10%,50V,SL,TP,6.5X		
AC2	2201-000368	C-CERAMIC,DISC;0.22NF,10%,50V,SL,TP,6.5X		
AC3	2201-000368	C-CERAMIC,DISC;0.22NF,10%,50V,SL,TP,6.5X		
AC4	2201-000368	C-CERAMIC,DISC;0.22NF,10%,50V,SL,TP,6.5X		
DC17	2201-000368	C-CERAMIC,DISC;0.22NF,10%,50V,SL,TP,6.5X		
KC18	2202-000780	C-CERAMIC,MLC-AXIAL;100nF,+80-20%,50V,Y5		
TC3	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP		
TC4	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP		
TC5	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP		
TC6	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP		
TC7	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP		
TC9	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP		
CJW2A	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP		
DD2ASIDE	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP		
FC1A	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP		
FC38	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP		
FC39	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP		
MJW71A	2202-000781	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP		
TC20	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3		
EMC2	2202-000796	C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP,3		
KC17	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,		
KC20	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,		
FREE	2202-000806	C-CERAMIC,MLC-AXIAL;220pF,10%,50V,Y5P,TP		
DVC1A	2202-000806	C-CERAMIC,MLC-AXIAL;220pF,10%,50V,Y5P,TP		
KC19	2202-000809	C-CERAMIC,MLC-AXIAL;3.3nF,20%,16V,Y5R,-,		
KC10	2202-000829	C-CERAMIC,MLC-AXIAL;0.82NF,10%,50V,Y5P,T		
KC15	2202-000854	C-CERAMIC,MLC-AXIAL;47nF,30%,50V,Y5R,TP,		
KC16	2202-000854	C-CERAMIC,MLC-AXIAL;47nF,30%,50V,Y5R,TP,		
DC23	2301-000370	C-FILM,LEAD-PEF;1.8nF,10%,50V,TP,5.5x12x		

Location no	Code no.	Description	Specifiation	Remarks
DC22	2301-000370	C-FILM,LEAD-PEF;1.8nF,10%,50V,TP,5.5x12x		
DC25	2301-000375	C-FILM,LEAD-PEF;100nF,5%,50V,TP,11x12.5x		
DC26	2301-000375	C-FILM,LEAD-PEF;100nF,5%,50V,TP,11x12.5x		
DC7	2301-000375	C-FILM,LEAD-PEF;100nF,5%,50V,TP,11x12.5x		
KC2	2301-000375	C-FILM,LEAD-PEF;100nF,5%,50V,TP,11x12.5x		
KC5	2301-000375	C-FILM,LEAD-PEF;100nF,5%,50V,TP,11x12.5x		
AC5	2301-000375	C-FILM,LEAD-PEF;100nF,5%,50V,TP,11x12.5x		
AC6	2301-000375	C-FILM,LEAD-PEF;100nF,5%,50V,TP,11x12.5x		
AC7	2301-000375	C-FILM,LEAD-PEF;100nF,5%,50V,TP,11x12.5x		
AC8	2301-000375	C-FILM,LEAD-PEF;100nF,5%,50V,TP,11x12.5x		
DC10	2301-000375	C-FILM,LEAD-PEF;100nF,5%,50V,TP,11x12.5x		
KC12	2301-000379	C-FILM,LEAD-PEF;10nF,10%,50V,TP,6x12x3.5		
KC11	2301-000379	C-FILM,LEAD-PEF;10nF,10%,50V,TP,6x12x3.5		
DC24	2301-000379	C-FILM,LEAD-PEF;10nF,10%,50V,TP,6x12x3.5		
DC11	2301-000379	C-FILM,LEAD-PEF;10nF,10%,50V,TP,6x12x3.5		
AC13	2301-000379	C-FILM,LEAD-PEF;10nF,10%,50V,TP,6x12x3.5		
AC11	2301-000379	C-FILM,LEAD-PEF;10nF,10%,50V,TP,6x12x3.5		
KC4A	2301-000387	C-FILM,LEAD-PEF;150nF,10%,50V,TP,12.5x15		
KC1A	2301-000387	C-FILM,LEAD-PEF;150nF,10%,50V,TP,12.5x15		
DC16	2301-000404	C-FILM,LEAD-PEF;2.2nF,10%,50V,TP,5.5x12x		
DC15	2301-000404	C-FILM,LEAD-PEF;2.2nF,10%,50V,TP,5.5x12x		
DC14	2301-000404	C-FILM,LEAD-PEF;2.2nF,10%,50V,TP,5.5x12x		
AC9	2301-000404	C-FILM,LEAD-PEF;2.2nF,10%,50V,TP,5.5x12x		
AC10	2301-000404	C-FILM,LEAD-PEF;2.2nF,10%,50V,TP,5.5x12x		
DC13	2301-000407	C-FILM,LEAD-PEF;2.7nF,10%,50V,TP,5.5x12x		
DC12B	2301-000407	C-FILM,LEAD-PEF;2.7nF,10%,50V,TP,5.5x12x		
DC12A	2301-000407	C-FILM,LEAD-PEF;2.7nF,10%,50V,TP,5.5x12x		
FREE	2301-000412	C-FILM,LEAD-PEF;22nF,10%,50V,TP,8x12x4mm		
PC4	2301-000449	C-FILM,LEAD-PEF;47nF,10%,50V,TP,9.5x12.5		
PC3	2301-000449	C-FILM,LEAD-PEF;47nF,10%,50V,TP,9.5x12.5		
KC14	2301-000474	C-FILM,LEAD-PEF;8.2nF,10%,50V,TP,6.5x12x		
HPC8	2401-000240	C-AL;100uF,20%,10V,GP,TP,5x11,5		
KCAA	2401-000303	C-AL;100uF,20%,25V,GP,TP,6.3x11,5		
FREE	2401-000303	C-AL;100uF,20%,25V,GP,TP,6.3x11,5		
DC30	2401-000414	C-AL;10uF,20%,16V,GP,TP,4x7,5		
KC3A	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5		
KC21	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5		
FREE	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5		
FC9	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5		
FC8	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5		
DC20	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5		
FC22	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5		
FC23	2401-000588	C-AL;1uF,20%,50V,GP,TP,3x5,2.5		
DC9	2401-000651	C-AL;2.2uF,20%,50V,GP,TP,4x7,5		
DVC2	2401-000651	C-AL;2.2uF,20%,50V,GP,TP,4x7,5		
DVC3	2401-000651	C-AL;2.2uF,20%,50V,GP,TP,4x7,5		
DVC5	2401-000651	C-AL;2.2uF,20%,50V,GP,TP,4x7,5		
FC18	2401-000651	C-AL;2.2uF,20%,50V,GP,TP,4x7,5		
FC19	2401-000651	C-AL;2.2uF,20%,50V,GP,TP,4x7,5		
AC12	2401-000651	C-AL;2.2uF,20%,50V,GP,TP,4x7,5		
DC27	2401-000651	C-AL;2.2uF,20%,50V,GP,TP,4x7,5		
DC28	2401-000651	C-AL;2.2uF,20%,50V,GP,TP,4x7,5		
DC34	2401-000651	C-AL;2.2uF,20%,50V,GP,TP,4x7,5		
DC6	2401-000651	C-AL;2.2uF,20%,50V,GP,TP,4x7,5		
DC8	2401-000651	C-AL;2.2uF,20%,50V,GP,TP,4x7,5		
FREE	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m		
DC2	2401-000778	C-AL;220uF,20%,10V,GP,-,6.3x11,2.5m		
FC36	2401-001020	C-AL;3.3UF,20%,50V,GP,TP,4X7,5		
FC35	2401-001020	C-AL;3.3UF,20%,50V,GP,TP,4X7,5		
FC34	2401-001020	C-AL;3.3UF,20%,50V,GP,TP,4X7,5		
FC1	2401-001020	C-AL;3.3UF,20%,50V,GP,TP,4X7,5		
DC36	2401-001020	C-AL;3.3UF,20%,50V,GP,TP,4X7,5		
AC15	2401-001080	C-AL;330nF,20%,50V,GP,-,5x11,2mm		
DC4	2401-001102	C-AL;330uF,20%,16V,GP,TP,8x11.5mm,5		
CC5	2401-001164	C-AL;33uF,20%,16V,GP,TP,5x11mm,5mm		
AC14	2401-001164	C-AL;33uF,20%,16V,GP,TP,5x11mm,5mm		
DC32	2401-001508	C-AL;47uF,20%,16V,GP,TP,6.3x5,5		
DC21	2401-001508	C-AL;47uF,20%,16V,GP,TP,6.3x5,5		
DC12	2401-001508	C-AL;47uF,20%,16V,GP,TP,6.3x5,5		
KC23	2401-001893	C-AL;100uF,20%,16V,GP,TP,6.3x7,5		
FREE	2401-001893	C-AL;100uF,20%,16V,GP,TP,6.3x7,5		
FC5	2401-001893	C-AL;100uF,20%,16V,GP,TP,6.3x7,5		
FREE	2401-001952	C-AL;4.7uF,20%,50V,GP,TP,5x7mm,5mm		
FC4	2401-001952	C-AL;4.7uF,20%,50V,GP,TP,5x7mm,5mm		
FC33	2401-001952	C-AL;4.7uF,20%,50V,GP,TP,5x7mm,5mm		
FC25	2401-001952	C-AL;4.7uF,20%,50V,GP,TP,5x7mm,5mm		
FC2	2401-001952	C-AL;4.7uF,20%,50V,GP,TP,5x7mm,5mm		
FREE	2401-002594	C-AL;220uF,20%,16V,GP,TP,8x11.5,5		
DL3	2701-000298	INDUCTOR-AXIAL;470uH,10%,4298		
	3602-000147	FUSE-CLIP;250V,7.5A,30mohm		
	AH41-00659A	PCB;MAX-VJ730/ZJ650,####,1 LAYER,-		
	AH97-01111A	ASSY-CA?DECK;-,MAX-S720,ASSY CA'DECK		
	6003-001446	SCREW-TAPTITE;BH,+,,M2,L5,NI PLT		
	AH39-00021A	LEAD CONNECTOR ASSY;UL1533#28,300MM,-,-,		
	AH39-20002D	LEAD CONNECTOR ASSY;5264,-,3P,300MM,2970		
	AH61-00413B	BRACKET-DECK;MAX-B550,SPTE 0.3T,0.3T,-,-		
	AH59-01145A	**DECK-CASSETTE;ADR268AMW1,MAXS560,-,-,DC1**		